

BOM monotropa v3**Reverselandfill 2020****Resistors**

f1, f2	10r	2	
r1, r8, r10, r15	1.8k	4	alt: 2k
r7	2k2	1	alt: 2k
r3, r4, r5, r6, r12, r13, r16	10k	7	
r19, r20, r21	1k	3	

Band combinations* see below for more info and mods

band1	low	
c1	1uf	5mm film
c6	22nF	5mm film
r2	130k	
band2	low-mid	
c7	470nf	5mm film
c9	10nf	5mm film
r9	110k	
band3	mid	
c8	82nf / 100nF	5mm film
c10	2.2nf	5mm film
r11	82k	
band4	mid-high	
c11	33nf	5mm film
c12	1nf	5mm film
r14	68k	

Capacitors

c2, c3	10uF	2	electrolythic
c13, c27, c28	1uf	3	electrolythic
c4, c5, c21, c23	100nF	4	in kit: mount vertically
c25	10pF	1	alt: 20pF

IC

u1, u2	14pin socket	2	
u1, u2	TL084	2	alt: tl074, tl064

Power

10 pin connector	shrouded	1	
power cable	10pin to 16pin	1	

Place the panel on the PCB before soldering the pots and jacks

Pots

band1, band2, band3, band4, gain, sum	b10k	6	vertical 9mm
---------------------------------------	------	---	--------------

Jacks

thonkiconn	6	vertical
------------	---	----------

Knobs

6

Blad1

*Alternative frequency bands: (you can use parts that are near these values)

63Hz	1270nF, 22nF, 130k
160Hz	503nF, 10nF, 110k
410Hz	200nF, 4.7nF, 91k
1KHz	80nF, 2.2nF, 82k
2.5KHz	33nF, 1nF, 68k
7.7KHz	12.2nF, 470pF, 62k
16KHz	4.7nF, 220pF, 51k

CC-BY-SA

credits: part of the EQ was inspired by the Musicthingmodular Graphic EQ / Boss GE7
The rest of the design (feedback loop, mixer amp stages, external routing, mods are by:

www.reverselandfill.org
martijn@reverselandfill.org